

External

# QFlood Residential

## PIR Remote Control

**QVIS**<sup>®</sup>  
LED LIGHTING

CODE: QFLOOD-PIR-REMOTE



For use with the QFlood  
Remote PIR Sensor  
[QFLOOD-PIR-RC]



**Press Once** - The light will turn off.



**Press Once** - The sensor will work to the default 24 hour operation settings. These are: 10s time delay and 100% detection range.



**Press Once** - The light will turn on.



**Press Once** - The sensor will be in 'Photocell' mode with dusk to dawn light operation.



**Time Delay Cycle** - Each press of this button cycles delay between 10s / 30s / 1min / 5min / 8min / 10min.



**Sensitivity Cycle** - Each press of this button cycles sensitivity between Low [30%] / Medium [60%] / High [100%].



**Lux Cycle** - Each press of this button cycles lux between Night [5Lx] / Low [30Lx] / Medium [100Lx] / High [200Lx] / Day [2000Lx].